

INSTALLATION GUIDE



PRE-INSTALLATION

Power input of 12V/24V AC/DC. Confirm the source voltage is compatible.
Disconnect power source prior to installation.

* Before installing, please check if there are signs of serious damage to the lamps.

* Customized product's installation method may differ and depend on its spec

INSTALLATION


STEP 1 Open package to remove fixture and preinstall box.

STEP 2 Place the install box to pre-dug hole. Pull the prepared main power supply out through the box and connect with the fixture wiring.

* The joint of the wiring connection between the main power and fixture must be IP68 waterproofed in case of water leakage, which may cause short circuit.

STEP 3 Test and ensure that all fixtures work. Put into preinstall box and press tightly.

DIMENSIONS



MODEL	LED FIXTURE		BURIAL SLEEVE		
	WIDTH	HEIGHT	WIDTH ¹	WIDTH ²	HEIGHT
IG-101	65.09mm	79.38mm	60.33mm	152.4mm	92.08mm
IG-102	65.09mm	79.38mm	60.33mm	152.4mm	92.08mm
IG-103-SS	∅ 55mm	79mm	∅ 48mm	∅ 85mm	97.2mm
IG-104-SS	∅ 55mm	79mm	∅ 48mm	∅ 85mm	97.2mm
IG-200-SS	∅ 55.6mm	60.3mm	∅ 55.6mm	∅ 100mm	100mm

SAFETY





Read all instructions before installation.

Do not take apart lighting fixture.

Do not look directly into light.

Lighting outlet and on-site power supply cable connection must have IP68 level protection, so as not to affect normal operation.

This fixture is only suitable for installation in dry or sunny weather.

-  Product should be installed in accordance with these instructions, current electrical codes, and/or current National Electric Code (NEC).
-  Not recommended to be installed on the beach and corrosive chemical areas to avoid corrosion and damage.
-  Product should only be installed and removed by a professional technician.
-  Product is 12V/ 24V. Do not connect to 120V power source.

